# Honeywell Home Keypads



The Honeywell Home 6160PX Custom Alpha Prox Keypad is easy to install and simple to use. The system can be armed away or disarmed with a single swipe of the proximity tag, making operation effortless while reducing false alarms. Prox keypad can be installed in hardwired or wireless installations. Security code is incorporated into the prox tag for easy enrollment.

The 6160PX also features a large, bright 32-character display with easy-to-read plain-English status messages. The oversized function keys are easily accessible even when the keypad door is closed, and can be programmed for fire, burglary, personal emergencies and other operations. Colored self-adhesive labels are included to easily identify one-button functions.



### FEATURES AND BENEFITS

- Integrated proximity reader
- Two lightweight tags included with user code already incorporated
- Arming (armed away) and disarming functions
- Large, easy-to-use keypad

- Keys continuously backlit for greater visibility
- Zones and system events displayed in plain English
- Speaker with audible beeps to indicate: System status Entry/exit delay Other alarm situations
- Four programmable function keys
- System functions clearly labeled
- White console blends with any décor

## 6160PX Technical Specifications

**Physical:** 5-5/16"H x 7-3/8" W x 1-3/16" D Wiring (135mm x 190mm x 30mm) - (Black): Ground **Displays:** 2 x 16 alpha-numeric + (Red): +12 VDC (Aux. Power) supertwist LCD, backlit D1 (Green): "Data in" to control panel Sounder: Speaker (fire alarm is loud, DO (Yellow): "Data out" from pulsing single tone; burglary alarm is control panel loud, continuous, dual-tone) Compatibility: Fully compatible with all Voltage: 12VDC (power-limited) addressable VISTA controls Current Agency Listings Activated transmission - 165mA **ETL Listings**: (ARMED LED lit, LCD backlight and Residential Fire and Burglary sounder on) Commercial Burglary Standby – reduces to 40mA when panel is operating in standby mode (backlight off)

### ORDERING

6160PX	Alpha Display Keypad with Integrated Proximity Reader
PROXTG-BK	Black Prox Tag
PROXTG-GY	Gray Prox Tag

#### For more information

security.honeywellhome.com/hsc



#### Resideo Technologies, Inc.

2 Corporate Center Drive, Suite 100 P.O. Box 9040 Melville, NY 11747 1-800-645-7492 resideo.com L/6160PXD/D | 06/19 © 2019 Resideo Technologies, Inc. This product is manufactured by Resideo and its affiliates. The Honeywell Home trademark is used under license from Honeywell International Inc. All rights reserved.

## Honeywell Home